# 5.0-5.8GHz 4000mW 36dBm WiFi Signal Booster

## SKU :0305SH100311 Model: SH58Gi4000P P/N: 58Gi4000014 Bar code: 6958917601275

#### Features:

5.8GHz, Max. 4000mW output power; Aluminum-alloy case by CNC, anti-interference; Small size, Safe & Power saving; Full kit, easy to install; For house, office, UAV, IP cameras, RC equipment....

#### **Technical Specifications:**

Booster model: SH58Gi4000 Operating range : 5000~5875MHz Channel width: 20Mhz&40Mhz&80Mhz Supported standards: IEEE 802.11a/n/ac Operation mode: Bi-directional, half-duplex, time division duplex Connector type: To radio SMA female (hole inside). To antenna RP-SMA female (pin inside) Output power: 4000mW (36dBm) Input power: 0 ~ 20dBm Transmit gain: 17 ~ 20dB Receiver gain: ≤12dB Noise figure: ≤3.5dB typical Frequency response: ±1dBoveroperatingrange Power adapter: 12V/2A DC, 100~240V Operating temperature: -20°C to +70°C Operating humidity: Up to 75% relative humidity Material: Cast aluminum LED light: Power status LED and activity status LED Booster weight: 133g Booster size: 9.7 x 6.4 x 1.7cm

### Package weight: 420g Package size: 21.3 x 13.5 x 5cm

#### Package contents:

- 1 x SH58Gi4000 WiFi booster
- 1 x RG316 cable with SMA connectors (20cm)
- 1 x 6dBi omni antenna
- 1 x power supply
- 1 x user manual

