5.0-5.8GHz 2000mW 33dBm WiFi Signal Booster

SKU: 0305SH100025 Model: SH58Gi2000P P/N: 58Gi2000014

Barcode: 6958917600353

Features:

5.8GHz, Max. 2000mW output power;

Aluminum-alloy case by CNC, anti-interference;

Small size, Safe & Power saving;

Full kit, easy to install;

For house, office, UAV, IP cameras, RC equipment....

Technical Specifications:

Booster Model: SH58Gi2000 Operating range: 5000~5875MHz Channel width: 20Mhz&40Mhz&80Mhz Supported standards: IEEE 802.11a/n

Operation mode: Bi-directional, half-duplex, time division duplex

Connector type: To radio SMA female (hole inside).

To antenna RP-SMA female (pin inside)

Output power: 2000mW (33dBm)

Input power: 0 ~ 20dBm Transmit gain: 15 – 18dB Receiver gain: 11 – 14dB Noise figure: ≤3.5dB typical

Frequency response: ±1dB over operating range

Power adapter: 12V/2A DC, 100~240V Operating temperature: -20°C to +70°C

Operating humidity: Up to 75% relative humidity

Material: Cast aluminum

LED light: Power status LED and activity status LED

Booster weight: 110g

Booster size: 8.4 x 5.4 x 2cm

Package weight: 390g

Package size: 21.3 x 13.5 x 5cm

Package contents:

1 x SH58Gi2000 WiFi booster

1 x RG316 cable with SMA connectors (20cm)

1 x 6dBi omni antenna

1 x power supply

1 x user manual

