

868MHz 1W 30dBm Booster

SKU:0305SH200802

Model: SH08Gi1000

Features:

868MHz, Max. 1000mW output power;
Aluminum-alloy case by CNC, anti-interference;
Small size, Safe & Power saving;
Full kit, easy to install;
For house, office, IP cameras, supermarkets....



Technical Specifications:

Booster Model: SH08Gi1000

Operating range : 863~870MHz

Channel width: 1-5Mhz

Supported standards:IEEE 802.11b/a/g/n

Operation mode: Bi-directional, half-duplex, time division duplex

Connector type: To radio SMA female (hole inside).

To antenna RP-SMA female (pin inside)

Output power: 1000mW (30dBm)

Input power: 0 ~ 23dBm

Transmit gain: 24dB typical

Receiver gain: 16dB typical

Noise figure: ≤3.5dB typical

Frequency response: ±1dB over operating range

Power adapter: 12V/2A DC, 100~240V

Operating temperature: -20°C to +70°C

Operating humidity: Up to 75% relative humidity

Material: Cast aluminum

LED light: Power status / activity status LED

Booster weight: 140g

Booster size: 9.7 x 6.4 x 1.7cm

Package contents:

1X SH08Gi1000 WiFi Booster

1X Power Supply