

Sunhans 2.4GHz&5.8GHz 4000mW Dual Band Indoor WiFi Signal Booster

SKU :0305SH200774

Model: SHPro5824G4W

P/N: Pro5824G4W019

Bar code: 6958917601916

Features:

2.4GHz&5.8GHz, Max. 4000mW output power;
Aluminum-alloy case by CNC, anti-interference;
For house, office, UAV, IP cameras, RC equipment....



Technical Specifications:

Booster model: SHPro5824G4W
Operating range : 2.4~2.5GHz; 5.0~5.8GHz
Channel width: 20Mhz&40Mhz&80Mhz
Supported standards: IEEE 802.11b/g/n/a/ac
Operation mode: Bi-directional, half-duplex, time division duplex
Connector type: N-K female
Output power: 4000mW (36dBm)
Input power: 0 ~ 20dBm
Transmit gain: 16 ~ 19dB
Receiver gain: ≤12dB
Noise figure: ≤3.5dB typical
Frequency response: ±1dB over operating range
Power adapter: 12V/2A DC, 100~240V
Operating temperature: -40°C to +70°C
Operating humidity: Up to 75% relative humidity
Material: Cast aluminum
LED light: Power status LED and activity status LED
Booster weight: 318g
Booster size: 13cm x 7.7cm x 2.4cm

Package weight:

Package size:

Package contents:

1 x SHPro5824G4W WiFi booster
1 x power supply
1 x user manual