

# Sunhans 2.4GHz&5.8GHz 4000mW Dual Band Outdoor WiFi Signal Booster

**SKU: 0305SH200780**

**Model: SHPro5824Go4W**

## **Features:**

2.4GHz&5.8GHz, Max. 4000mW output power;  
Aluminum-alloy case by CNC, anti-interference;  
For house, office, UAV, IP cameras, RC  
equipment....



## **Technical Specifications:**

Booster model: SHPro5824Go4W  
Operating range : 2.4~2.5GHz; 5.0~5.8GHz  
Channel width: 20Mhz&40Mhz&80Mhz  
Supported standards: IEEE 802.11b/g/n/a/ac  
Operation mode: Bi-directional, half-duplex, time division duplex  
Connector type: N-K female  
Output power: 4000mW (36dBm)  
Input power: 0 ~ 20dBm  
Transmit gain: 16 ~ 19dB  
Receiver gain: ≤12dB  
Noise figure: ≤3.5dB typical  
Frequency response: ±1dB over operating range  
Power adapter: 12V/2A DC, 100~240V  
Operating temperature: -40°C to +70°C  
Operating humidity: Up to 75% relative humidity  
Material: Cast aluminum  
LED light: Power status LED and activity status LED  
Booster weight: 318g  
Booster size: 13cm x 7.7cm x 2.4cm

**Package weight:**

**Package size:**

## **Package contents:**

1 x SHPro5824Go4W WiFi booster

1 x feeding box

1 x power supply

1 x user manual